

Multi-channel Analog Input Card for PCI AD12-64(PCI)



* Specifications, color and design of the products are subject to change without notice.

Features

Multi-channel analog input

This product can perform an analog input of single-ended input 64 channels and differential input 32 channels. Selection of single-ended input and differential input can be set up by the software.

Input range setup by software

Input range can be selected for each channel from the following ranges and can be set up by the software.
±10V, ±5V, ±2.5V, ±1.25V, 0 - +10V, 0 - +5V, 0 - +2.5V, 0 - +1.25V

Sampling control function

This product can perform sampling either at arbitrary timings under control of software or periodically in synchronization with a sampling clock signal.

The sampling clock signal can be selected between the internal one based on the on-board clock generator and the external one using a digital signal input from an external source.

Digital input/output function

This product has four digital input and four digital output pins for TTL-level signals, allowing an external device to be monitored and controlled.

Optional units

Using optional units facilitates connections.

For more details on the option, please refer to "Cable & Connector" or "Accessories (Option)".

Included Items

Board [AD12-64(PCI)] ...1
Please read the following ... 1

This product is PCI-compliant interface boards that convert analog input signals to digital equivalents (performing analog-to-digital conversion).

This product can perform A-D conversion at a conversion speed of 10μsec[100KSPS] per channel and a resolution of 12bit.

Using the bundled driver library [API-PAC(W32)], you can create Windows application software for this board in your favorite programming language supporting Win32 API functions, such as Visual Basic or Visual C++.

- * The contents in this document are subject to change without notice.
- * Visit the CONTEC website to check the latest details in the document.
- * The information in the data sheets is as of October, 2022.

Specifications

Item	AD12-64(PCI)
Analog input	
Isolated specification	Non-isolation
Input Type	Single-Ended Input or Differential Input (Software setup)
Number of input channels	64 channels (Single-Ended Input), 32 channels (Differential Input)
Input range	Bipolar ±10V, ±5V, ±2.5V, ±1.25V, or Unipolar 0 - +10V, 0 - +5V, 0 - +2.5V, 0 - +1.25V (Software setup per channel)
Absolute max. input voltage	±15V
Input impedance	1MΩ or more
Resolution	12bit
Non-Linearity error *1	±2LSB(±10V, ±5V, 0 - 10V, 0 - 5V), 4LSB(±2.5V, ±1.25V, 0 - 2.5V) ±8LSB(0 - 1.25V)
Conversion speed	10μsec [100KSPS]/ch (Max)
Sampling clock	Internal sampling clock: 10,000 - 1,073,741,824,000nsec (Settable in 250 nanoseconds) External sampling clock: TTL level falling edge
Digital I/O	
Number of output channels	4 TTL levels
Number of input channels	4 TTL levels
Programmable timer	
Setting period	500 - 1,073,741,824,000nsec (Settable in 250 nanoseconds)
Status	Count up, count up over run
Timer output signal	TTL-level 250nsec Low pulse, Low level output current I _{OL} = 24mA
External trigger input	
External trigger input signal	Non-isolated input 1 channel (TTL-level falling edge)
Status	Trigger input, trigger input overrun
I/O address	32 ports boundary
Interrupt level	1 level use
Operating condition	0 - 50°C, 10 - 90%RH (No condensation)
Current consumption *2	+5VDC 700mA (Max)
Bus specification	32bit, 33MHz, Universal key shapes supported *3*4
Connector	96-pin half pitch connector [M(male) type] PCR-E96LMD+ [HONDA TSUSHIN KOGYO CO., LTD.] or equivalence to it
Dimension (mm)	176.41(L) x 105.68(H) *5
Weight	150g
Standard	VCCI Class A, CE Marking (EMC Directive Class A, RoHS Directive), KC, UKCA

*1 A linearity error approximately 0.1% of full-range may occur when operated at 0°C or 50°C ambient temperature. The error can be reduced by calibrating under the actual temperature conditions.


*2 If an external device requires this AD12-16(PCI) product to supply +5VDC from the CN1 or CN2 connectors, the power consumption of this product will be bigger than what this specification has defined.

*3 This product requires +5V power supply from expansion slots (it does not operate in the environment of only +3.3V power supply).

*4 AD12-64(PCI): If the board No. is No.7149A, PCI bus specification is 32bit, 33MHz, 5V.

*5 Boards with different board numbers are different in these specifications. See "Different in the specification" at the end of this document.

Board Dimensions



The standard outside dimension (L) is the distance from the end of the board to the outer surface of the slot cover.

Support Software

Windows version of digital I/O driver API-AIO(WDM)

The API-AIO(WDM) is the Windows version driver library software that provides products in the form of Win32 API functions (DLL). Various sample programs such as Visual Basic and Visual C++, etc and diagnostic program useful for checking operation is provided.

For more details on the supported OS, applicable language and how to download the updated version, please visit the CONTEC's Web site.

Linux version of digital I/O driver API-AIO(LNX)

The API-AIO(LNX) is the Linux version driver software which provides device drivers (modules) by shared library and kernel version. Various sample programs of gcc are provided.

For more details on the supported OS, applicable language and how to download the updated version, please visit the CONTEC's Web site.

LabVIEW VI Library for Data Acquisition DAQfast for LabVIEW

This is a data collection library to use our devices in the LabVIEW by National Instruments. With Polymorphic VI, our design enables a LabVIEW user to operate seamlessly. Our aim is for the customers to perform easily, promptly what they wish to do.

For more details on the library and download of DAQfast for LabVIEW, please visit the CONTEC's Web site.

Cable & Connector

Cable (Option)

Shield Cable with 96-Pin Half-Pitch Connectors at Both Ends
: PCB96PS-0.5P (0.5m), PCB96PS-1.5P (1.5m)

Flat Cable with 96-Pin Half-Pitch Connectors at Both Ends
: PCB96P-1.5 (1.5m)

Shield Cable with 96-Pin Half-Pitch Connectors at One End
: PCA96PS-0.5P (0.5m), PCA96PS-1.5P (1.5m)

Flat Cable with 96-Pin Half-Pitch Connectors at One End
: PCA96P-1.5 (1.5m)

Accessories

Accessories (Option)

Terminal Unit for Cables (M3 x 96P) : DTP-64A *1
Screw Terminal Unit (M3.5 x 96P) : EPD-96 *1
Screw Terminal Unit (M3 x 96P) : EPD-96A *1*4

1 PCB96P- or PCB96PS-* optional cable is required separately.

*2 "Spring-up" type terminal is used to prevent terminal screws from falling off.

Different in the specification

The AD12-64(PCI) is different in specifications, depending on the board number as listed below.

AD12-64(PCI)

Board No.	No.7149A	No.7149B	No.7149D
Dimension (mm)	176.41(L)×106.68(H)	176.41(L)×106.68(H)	176.41(L)×105.68(H)

Connector Pin Assignment

Single-Ended Input


Analog Input 63	B48	A48	Analog Input 59
Analog Input 55	B47	A47	Analog Input 51
Analog Input 62	B46	A46	Analog Input 58
Analog Input 54	B45	A45	Analog Input 50
Analog Input 61	B44	A44	Analog Input 57
Analog Input 53	B43	A43	Analog Input 49
Analog Input 60	B42	A42	Analog Input 56
Analog Input 52	B41	A41	Analog Input 48
Analog Ground	B40	A40	Analog Ground
Analog Ground	B39	A39	Analog Ground
Analog Input 47	B38	A38	Analog Input 43
Analog Input 39	B37	A37	Analog Input 35
Analog Input 46	B36	A36	Analog Input 42
Analog Input 38	B35	A35	Analog Input 34
Analog Input 45	B34	A34	Analog Input 41
Analog Input 37	B33	A33	Analog Input 33
Analog Input 44	B32	A32	Analog Input 40
Analog Input 36	B31	A31	Analog Input 32
Analog Ground	B30	A30	Analog Ground
Analog Ground	B29	A29	Analog Ground
Analog Input 31	B28	A28	Analog Input 27
Analog Input 23	B27	A27	Analog Input 19
Analog Input 30	B26	A26	Analog Input 26
Analog Input 22	B25	A25	Analog Input 18
Analog Input 29	B24	A24	Analog Input 25
Analog Input 21	B23	A23	Analog Input 17
Analog Input 28	B22	A22	Analog Input 24
Analog Input 20	B21	A21	Analog Input 16
Analog Ground	B20	A20	Analog Ground
Analog Ground	B19	A19	Analog Ground
Analog Input 15	B18	A18	Analog Input 11
Analog Input 7	B17	A17	Analog Input 3
Analog Input 14	B16	A16	Analog Input 10
Analog Input 6	B15	A15	Analog Input 2
Analog Input 13	B14	A14	Analog Input 9
Analog Input 5	B13	A13	Analog Input 1
Analog Input 12	B12	A12	Analog Input 8
Analog Input 4	B11	A11	Analog Input 0
Analog Ground	B10	A10	Analog Ground
Analog Ground	B09	A09	Analog Ground
+5VDC from PC	B08	A08	External Sampling Clock Input
+5VDC from PC	B07	A07	Digital Ground
Sampling Busy Output	B06	A06	External Trigger Input
Timer Output	B05	A05	Digital Ground
Digital Output 3	B04	A04	Digital Input 3
Digital Output 2	B03	A03	Digital Input 2
Digital Output 1	B02	A02	Digital Input 1
Digital Output 0	B01	A01	Digital Input 0

- The numbers in square brackets [] are pin numbers designated by HONDA TSUSHIN KOGYO CO.

Analog Input 0 - Analog Input 63	Analog input signal at the time of Single-Ended Input. The numbers correspond to channel numbers.
Analog Ground	Common analog ground for analog input signals.
Digital Input 0 - Digital Input 3	Digital input signal.
Digital Output 0 - Digital Output 3	Digital output signal.
External Trigger Input	External trigger input signal.
External Sampling Clock Input	External Sampling Clock Input signal.
Timer Output	Programmable timer output signal.
Sampling Busy Output	Output signal indicating that the board is performing AD conversion.
+5VDC from PC	Output +5V. The total current-carrying capacity that can be supplied from two pins is 1 A.
Digital Ground	Digital ground common to those signals other than analog input signals, such as digital I/O signals and external sampling clock input signals, and "+5V DC from PC".

Differential Input

Analog Input 31 [-]	B48		A48	Analog Input 27 [-]
Analog Input 31 [+]	B47		A47	Analog Input 27 [+]
Analog Input 30 [-]	B46		A46	Analog Input 26 [-]
Analog Input 30 [+]	B45		A45	Analog Input 26 [+]
Analog Input 29 [-]	B44		A44	Analog Input 25 [-]
Analog Input 29 [+]	B43		A43	Analog Input 25 [+]
Analog Input 28 [-]	B42		A42	Analog Input 24 [-]
Analog Input 28 [+]	B41		A41	Analog Input 24 [+]
Analog Ground	B40		A40	Analog Ground
Analog Ground	B39		A39	Analog Ground
Analog Input 23 [-]	B38		A38	Analog Input 19 [-]
Analog Input 23 [+]	B37		A37	Analog Input 19 [+]
Analog Input 22 [-]	B36		A36	Analog Input 18 [-]
Analog Input 22 [+]	B35		A35	Analog Input 18 [+]
Analog Input 21 [-]	B34		A34	Analog Input 17 [-]
Analog Input 21 [+]	B33		A33	Analog Input 17 [+]
Analog Input 20 [-]	B32		A32	Analog Input 16 [-]
Analog Input 20 [+]	B31		A31	Analog Input 16 [+]
Analog Ground	B30		A30	Analog Ground
Analog Ground	B29		A29	Analog Ground
Analog Input 15 [-]	B28		A28	Analog Input 11 [-]
Analog Input 15 [+]	B27		A27	Analog Input 11 [+]
Analog Input 14 [-]	B26		A26	Analog Input 10 [-]
Analog Input 14 [+]	B25		A25	Analog Input 10 [+]
Analog Input 13 [-]	B24		A24	Analog Input 9 [-]
Analog Input 13 [+]	B23		A23	Analog Input 9 [+]
Analog Input 12 [-]	B22		A22	Analog Input 8 [-]
Analog Input 12 [+]	B21		A21	Analog Input 8 [+]
Analog Ground	B20		A20	Analog Ground
Analog Ground	B19		A19	Analog Ground
Analog Input 7 [-]	B18		A18	Analog Input 3 [-]
Analog Input 7 [+]	B17		A17	Analog Input 3 [+]
Analog Input 6 [-]	B16		A16	Analog Input 2 [-]
Analog Input 6 [+]	B15		A15	Analog Input 2 [+]
Analog Input 5 [-]	B14		A14	Analog Input 1 [-]
Analog Input 5 [+]	B13		A13	Analog Input 1 [+]
Analog Input 4 [-]	B12		A12	Analog Input 0 [-]
Analog Input 4 [+]	B11		A11	Analog Input 0 [+]
Analog Ground	B10		A10	Analog Ground
Analog Ground	B09		A09	Analog Ground
+5VDC from PC	B08		A08	External Sampling Clock Input
+5VDC from PC	B07		A07	Digital Ground
Sampling Busy Output	B06		A06	External Trigger Input
Timer Output	B05		A05	Digital Ground
Digital Output 3	B04		A04	Digital Input 3
Digital Output 2	B03		A03	Digital Input 2
Digital Output 1	B02		A02	Digital Input 1
Digital Output 0	B01		A01	Digital Input 0



- The numbers in square brackets [] are pin numbers designated by HONDA TSUSHIN KOGYO CO.,

Analog Input 0 [+]	Analog input signal at the time of Differential Input.
Analog Input 31 [+]	The numbers correspond to channel numbers.
Analog Input 0 [-]	Analog input signal at the time of Differential Input.
Analog Input 31 [-]	The numbers correspond to channel numbers.
Analog Ground	Common analog ground for analog input signals.
Digital Input 0 - Digital Input 3	Digital input signal.
Digital Output 0 - Digital Output 3	Digital output signal.
External Trigger Input	External trigger input signal.
External Sampling Clock Input	External Sampling Clock Input signal.
Timer Output	Programmable timer output signal.
Sampling Busy Output	Output signal indicating that the board is performing AD conversion.
+5VDC from PC	Output +5V. The total current-carrying capacity that can be supplied from two pins is 1 A.
Digital Ground	Digital ground common to those signals other than analog input signals, such as digital I/O signals and external sampling clock input signals, and "+5V DC from PC"